KAKB-021A-CAV

HCFC, R-22, 60Hz, 1- Phase, 208/230 V

High Temp

Production Status:

This model is obsolete and is no longer in production for both OEM and service replacement. Please contact Customer Service about possible replacement models.

Performance

Evap(°F)/Cond(°F)	45 / 130	20 / 120
RG(°F)/Liq(°F)	65.0 / 130.0	65.0 / 120.0
Capacity (Btu/hr) Power (Watts):	21800 2290	13500 1840
Current (Amps):	11.00	9.00
EER (Btu/Wh):	9.50	7.30
Mass Flow (lbs/hr):	344	197

Sound Power (dBA):

Vibration (mils(peak-peak)):

Record Date:

2007-01-03

Mechanical

Number of Cylinders:	2	Displ(in^3/Rev):	4.20
Bore Size(in):	1.69	Displ(ft^3/hr):	255.09
Stroke(in):	0.94		
Overall Length (in):	14.38	Mounting Length (in):	8.19
Overall Width (in):	9.50	Mounting Width (in):	6.38
Overall Height (in):	10.44	Mounting Height (in):	11.19 *
Suction Size (in):		7/8 Sweat	

Discharge Size (in): 1/2 Flare
Oil Recharge (oz): 20
Initial Oil Charge (oz): 22

Net Weight (lbs):
Internal Free Volume (in^3):

Horse Power:

User Description

*Overall compressor height on Copeland Brand Product's specified mounting grommets.

106

Electrical

LRA-High*:	55.0	MCC (Amps):	14.8	UL File No:	SA-2337
LRA-Half Winding:		RPM:	3500	UL File Date:	23-Jul-1984

LRA Low*: Max Operating Current:

RLA(=MCC/1.4;use for contactor selection): 10.6
RLA(=MCC/1.56;use for breaker & wire size selection): 9.5

*Low and High refer to the low and high nominal voltage ranges for which the motor is approved.

4.76 Max

 Type
 Part No
 Low MFD
 High MFD
 Volts

 Start Capacitor
 014-0061-30
 130.0
 156.0
 330

 Run Capacitor
 014-0064-14
 40.0
 0.0
 440

Alternate Applications

Refrigerant	Freq (Hz)	Phase	Voltage	Application
R-12 CFC	50	1	200/220	UL Medium Temp
R-22 HCFC	50	1	200/220	High Temp
R-22 HCFC	50	1	200/220	Low Temperature
R-22 HCFC	50	1	200/220	Medium Temperature
R-507 HFC	50	1	200/220	
R-12 CFC	60	1	208/230	UL Medium Temp
R-22 HCFC	60	1	208/230	Low Temperature
R-22 HCFC	60	1	208/230	Medium Temperature
R-507 HFC	60	1	208/230	

Public CROPI Public

02/11/2015

Page 1 Of 1